

POWERTEC

PORTABLE POWER SOLUTIONS

PT6600ES PORTABLE GENERATOR

ELECTRIC START

7000W PEAK POWER.

IDEAL FOR SERIOUS JOBS ONSITE AND FIELD EVENTS

AC & DC OUTPUTS - great for 240V applications like operating lighting whilst the 12V option is suitable for charging car batteries.

DURABLE STEEL ROLL CAGE FRAME AND PROFESSIONAL ANTI-VIBRATION MOUNT SYSTEM.

LARGE CAPACITY MUFFLER FOR QUIET OPERATION - minimizes engine noise to 72dBA, making this generator ideal for use anywhere a quiet source of electrical power is required.

SUPERIOR QUALITY ALTERNATOR AND AUTOMATIC VOLTAGE REGULATOR (AVR) - for more stable power output

LONG RANGE 25 LITRE FUEL TANK - ensures up to 8.5 hours of continuous operation.

ELECTRIC KEY START SYSTEM - for quick and easy startup (12V Powertec Battery # PTB18HD included)

HIGH PERFORMANCE AIR CLEANER SYSTEM - greatly reduces engine wear and improves performance.

INTEGRATED AC AND DC CIRCUIT BREAKERS - cut the power in the event of an electrical overload offering greater safety.

AC Output: 240V AC ~ 50Hz

DC Output: 12V DC Max 8A

Rated Power: 6500W

Peak Power: 7000W

Phase: Single

Displacement: 389CC

Engine: 13HP OHV Engine

Nominal Speed: 3000RPM

Fuel Tank Capacity: 25L Long Range

Fuel: Unleaded

Operation Noise Level: 72dB/7m

Net Weight: 88kg



IMPORTANT NOTICE: The Powertec Generator Series are NOT guaranteed to run sensitive electronic equipment like computers, TVs or other electronic appliances. For powering sensitive electronics an Inverter Generator is recommended. Ask your POWERTEC distributor for details.

7000W PEAK POWER